

Transmitters and Receivers Rack Mounting Instructions

The Terra transmitters and Receivers are rack mountable or under table mountable.

The TXO/RXO Rack Mount Shelf (166-111104-01) is a one unit (1U) high full-width rack shelf for securing Terra Transmitter (Terra TXO 102 SO) or Terra Receiver (RXO 101 SO) units. The rack shelf dimensions and perforations keep air vents open on the Terra units, and support efficient access to rear connectors when equipment is densely packed in a rack.

Christie does not provide rack rails or racks for mounting the shelves. Racks or rack rails should be purchased independently. The shelf is compatible with standard 19" equipment racks.

To rack mount a unit

1. Obtain rack mounting screws, clips and washers as required to secure equipment into equipment rack rails.
2. Place the Terra units onto the shelf.
3. Using the supplied screws, secure the Terra units to the shelf by inserting the screws through the beveled holes in the shelf and securing them to the bottom of the units.
4. Supporting the bottom of the rack, insert the rack screws through the holes in the Terra Rack Mount Shelf into the threaded holes in the rack rails.
5. Tighten the screws to secure the shelf.

